

Intrinsically Safe - Dust LIPS® SERIES E112	Part Number Coding					
	E112	Travel	A	Blank	Conn / Cable and Length	Z000
Gauge Head Linear Sensor						
Travel						
mm of stroke	5-50 mm	Value				
Electrical Interface						
Input		Output				
+ 5 V dc		See below		A		
Adjusts not available						
Connector / Cable						
Axial M12 Connector		J				
Connector - Radial		K				
Axial 3 Core Cable	Please specify cable length in cm.	Lxx		eg. L2000 specifies 20 metres of 3 core cable with an axial cable gland		
Axial 5 Core Cable	Please specify cable length in cm.	LQxx		eg. LQ2000 specifies 20 metres of 5 core cable with an axial cable gland		
Tighter Linearity			Zsuffix			
± 0.1% Linearity	from 10mm stroke only	Z650				

Please Note: This sensor *must* be used with a Galvanic Isolation Amplifier - See X005 sheet for Output options.